

DIMMER COMPATIBILITY STAR+ GLOWdim, PAR16 CRI97

BASIC INFORMATION:

1. WHAT IS THE PRODUCT CODE AND WHERE DO I FIND IT?

The product code describes the lamp type. It contains 7 letters and digits and is starting with "A". Below an example for the product code of the stamp of the lamp:



220-240V **AC01770** 2700K
13 W 50/60 Hz 27 mA
Made in Germany XXX-XXXX

2. HOW CAN I READ THE FOLLOWING CHARTS?

Legend:
Information about the dimmability of the lamps. Green means very good dimmability, yellow means limited dimmability, red means undesired dimmability etc.

List of dimmers tested in laboratory conditions

Legend					PARATHOM DIM CLP 2.5 Glass Frosted	PARATHOM DIM CLP 25 FIL	PARATHOM DIM CLP 40 Frosted	PARATHOM DIM CLP 40
Very good dimmability with indicated number of lamps (dimmability range greater than 75%)								
Limited dimmability with indicated number of lamps (dimmability range between 75%)								
Undesired dimmability								
Not relevant								
Dimmer					Basic Code	Basic Code	Basic Code	Basic Code
Brand	Model	Voltage range	Power	Type	2.5 Glass Frosted	25 FIL	40 Frosted	40
ABB	STO 5.0-2	230/50 Hz	60-500	L	100-2%	100-2%	100-2%	100-2%
Altenburger	S.O.2	230/50 Hz		U	100-2%	100-2%	100-2%	100-2%
AURORA	DSP 4.00	230/50 Hz	4.00	R	100-2%	100-2%	100-2%	100-2%
Berker	2R 61	230/50 Hz	5.0-42.0	U	95-10%	95-10%	95-10%	95-10%
Stelco	NT44.02.N	230/50 Hz	5.00	R	100-2%	100-2%	100-2%	100-2%
Stelco	NT44.02.HC (40/42.4)	230/50 Hz			100-2%	100-2%	94-6%	95-2%
Stelco	L/N/NT44.11.N	230/50 Hz			100-2%	100-2%	94-6%	95-2%
Suchtsieger	22.50 U	230/50 Hz	60-600	L	100-2%	100-2%	100-2%	100-2%
Suchtsieger	6512 U-10.2	230/50 Hz	4.20	T	100-2%	100-2%	100-2%	100-2%
Suchtsieger	6512 U	230/50 Hz			100-2%	100-2%	100-2%	100-2%
Suchtsieger	6512 U-10.2	230/50 Hz	4.0-42.0	T	100-2%	100-2%	100-2%	100-2%
CRISTAL CONTROL	MULTI DIMMER	230/50 Hz	60-600	U	95-2%	95-2%	95-2%	95-2%
DIMMY	RE 61.1 LED	230/50 Hz	4.00	LED	100-2%	100-2%	95-4%	95-4%
ELKO	40.02.L	230/50 Hz			99-2%	99-2%	99-2%	99-2%
ELKO	215.01.E	230/50 Hz	20-	T	100-2%	100-2%	100-2%	100-2%
ELKO	60.02.L	230/50 Hz	4.0-60.0	U	100-2%	100-2%	100-2%	100-2%
ELKO	41.02.L	230/50 Hz	4.0-42.0	U	100-2%	100-2%	94-6%	97-2%

Information about the OSRAM lamp type

Assessment of the results into categories. Includes the number of lamps and the related dimming range

DIMMER KOMPATIBILITÄT STAR+ GLOWdim, PAR16 CRI97

BASISINFORMATIONEN:

1. WAS IST DER PRODUKTCODE UND WO FINDE ICH IHN?

Der Produktcode beschreibt den Lampentyp. Er besteht aus sieben Buchstaben und Ziffern und beginnt mit einem "A". Nachfolgend ein Beispiel eines Produktcodes auf dem Aufdruck der Lampe.



220-240V **AC01770** 2700K
 13 W 50/60 Hz 27 mA
 Made in Germany XXX-XXXX

2. WIE LESE ICH DIE FOLGENDEN TABELLEN?

Legende: Angaben zur Dimmbarkeit der Lampen. Grün bedeutet eine sehr gute Dimmbarkeit mit der angegebenen Lampenanzahl, gelb bedeutet eine eingeschränkte Dimmbarkeit, rot bedeutet, dass unerwünschtes dimmverhalten auftreten kann etc.










Liste der getesteten Dimmer

Legend					PARATHOM DIM CLP			
					25 Glass Frosted	25 FIL	40 Frosted	40
Very good dimmability with indicated number of lamps (minimum range at least 75%)								
Limited dimmability with indicated number of lamps (minimum range at least 75%)								
Undesired dimmability								
Not relevant								
Dimmer					AC01770-50 / AC01770-60	AC01770-50 / AC01770-60	AC01770-50 / AC01770-60	AC01770-50 / AC01770-60
Brand	Model	Voltage range	Power	Type	1 lamp	2 lamp	3 lamp	4 lamp
ABB	STO 50-3	230/50 Hz	60-500 L	L	95-10%	95-10%	95-10%	95-10%
Alemburger	S.O.3	230/50 Hz		T	100-2%	100-2%	100-2%	100-2%
AURORA	OSP 400	230/50 Hz	400 R	R	95-10%	95-10%	95-10%	95-10%
Beimar	28 61	230/50 Hz	50-420 U	U	100-2%	100-2%	100-2%	100-2%
Belcho	NT44 02 U	230/50 Hz	500 R	R	100-2%	100-2%	100-2%	100-2%
Belcho	NT44 08 HC (H0, H54)	230/50 Hz		U	100-2%	100-2%	100-2%	100-2%
Belcho	L/N/NT44 11N	230/50 Hz		U	100-2%	100-2%	100-2%	100-2%
Busch-Jaeger	21 50 U	230/50 Hz	60-600 L	L	100-2%	100-2%	100-2%	100-2%
Busch-Jaeger	651 3 U-10 2	230/50 Hz	420 T	T	100-2%	100-2%	100-2%	100-2%
Busch-Jaeger	66 28 U	230/50 Hz		T	100-2%	100-2%	100-2%	100-2%
Busch-Jaeger	651 3 U-10 2	230/50 Hz	40-420 T	T	100-2%	100-2%	100-2%	100-2%
CEINSTEIN	CONTR OL	230/50 Hz	60-600 U	U	95-2%	95-2%	95-2%	95-2%
CLINGY	66 61 L 62	230/50 Hz	400 LED	LED	100-2%	100-2%	100-2%	100-2%
ELKO	40 OGLI	230/50 Hz		U	100-2%	100-2%	100-2%	100-2%
ELKO	215 GLE	230/50 Hz	30- T	T	100-2%	100-2%	100-2%	100-2%
ELKO	60 OGLI	230/50 Hz	40-600 U	U	100-2%	100-2%	100-2%	100-2%
ELKO	42 OGLI	230/50 Hz	40-420 U	U	100-2%	100-2%	100-2%	100-2%

Angaben zum OSRAM Lampentyp










Bewertung der Testergebnisse in Ampel Kategorien. Beinhaltet sowohl die Lampenanzahl als auch den dimmbaren Bereich

DIMMER COMPATIBILITY STAR+ GLOWdim, PAR16 CRI97

Legend					STAR+ MR16 35 GLOWdim	STAR+ PAR16 50 GLOWdim 36°	Star+ CL A GLOWdim	Star+ CL A 60 GLOWdim	Star+ CL B / BA Filament GLOWdim	STAR+ CL P GLOWdim	STAR+ Edison GLOWdim	STAR+ Globe GLOWdim	STAR+ PAR16 50 CRI97										
Very good dimmability with indicated number of lamps (dimming range greater than 75%)																							
Limited dimmability with indicated number of lamps (dimming range smaller than 75%)																							
Undesired dimmability																							
Not tested																							
					EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code										
					4058075105331 / AC08773	4058075105393 / AC08774	4058075808522 / AC02140	4058075037526 / AC02143	4058075808140 / AC02154 4058075809024 / AC02155	4058075809055 / AC02228	4058075808201 / AC02156	4058075808942 / AC02157	4058075035553 / AC08013										
Dimmer					Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps					
Brand	Model	Voltage range	Power	Type																			
ABB	STD 50-3	230/50Hz	60-500	L	89-0%		82-29%	100-23%	97-27%	81-20%	96-24%		94-26%		94-26%	81-20%	96-24%						
Altenburger	50,3	230/50Hz			100-0%	100-22%		89-21%		99-14%	98-24%	98-13%	100-37%	94-15%	100-37%	94-15%	98-24%	98-13%	98-24%	98-13%	2-20	100-17%	
AURORA	DSP 400	230/50Hz	400	R			88-4%	89-0%			98-0%	97-0%				98-0%	97-0%				1-3	100-0%	
Berker	2861	230/50Hz	50-420	U		100-26%		91-33%	99-42%	100-27%	96-22%	97-20%	99-36%	94-28%	99-36%	94-28%	96-22%	97-20%	96-22%	97-20%	1-20	100-34%	
Bticino	L/N/NT4411N	230/50Hz			94-11%		80-8%	80-8%	98-10%	97-3%	93-8%	88-3%	95-7%	94-3%	95-7%	94-3%	93-8%	88-3%	93-8%	88-3%	1-10	99-9%	
Bticino	L/N/NT4408	230/50Hz				100-0%					97-0%	96-0%		95-0%		95-0%	97-0%	96-0%			1-12	100-0%	
bticino	NT4402N	230/50Hz	500	R		100-40%		78-21%													1-12	98-27%	
Busch-Jaeger	6523 U-102	230/50Hz	40-420	T	99-13%		84-27%	84-28%	99-12%	99-12%	98-9%	99-9%	99-11%	98-8%	99-11%	98-9%	99-9%	98-9%	99-9%	98-9%	1-10	100-37%	
Busch-Jaeger	6513 U-102	230/50Hz	420	T	99-22%	99-30%	96-35%	96-25%	99-48%	100-21%	99-31%	98-15%	96-39%	94-21%	96-39%	94-21%	99-31%	98-15%	99-31%	98-15%	2-20	100-24%	
Busch-Jaeger	2250 U	230/50Hz	60-600	L	90-0%		90-16%	91-19%	100-8%	100-12%	99-8%	95-12%	100-11%	94-13%	100-11%	94-13%	99-8%	95-12%	99-8%	95-12%	1-4	100-24%	
Busch-Jaeger	6526 U	230/50Hz				100-62%	85-30%	84-30%															
CENTURY CONTROL	MULTI DIMMER	230/50Hz	60-600	U	95-0%	100-0%	89-13%	89-10%	100-10%	100-15%	98-9%	99-12%	99-7%	100-14%	99-7%	100-14%	98-9%	99-12%	98-9%	99-12%	1-7	100-17%	
DINUY	RE EL1 LE1	230/50Hz	400	LED	100-0%	100-0%	97-6%	97-6%													1-7	100-4%	
ELKO	400GLJ	230/50Hz				96-0%	87-12%		96-4%	99-0%	97-1%	97-0%	94-4%	98-0%	94-4%	98-0%	97-1%	97-0%	97-1%	97-0%	1-2	100-2%	
ELKO	315GLE	230/50Hz	20-315	T	100-15%	100-22%	93-30%	90-26%	99-33%		98-26%	99-21%	98-37%	98-26%	98-37%	98-26%	98-26%	99-21%	98-26%	99-21%	1-20	100-30%	
ELKO	600GLE/I	230/50Hz				100-0%	85-2%				97-0%	96-25%				97-0%	96-25%	97-0%	96-25%	1-6	100-0%		
ELKO	600GLI	230/50Hz	40-600	U		100-0%	86-21%				97-0%	97-0%					97-0%	97-0%			1-6	100-0%	
ELKO	420GLE/I	230/50Hz	40-420	U	99-21%	100-7%	85-11%	84-7%													1-9	100-7%	
ELKO	1000LRI	230/50Hz				100-0%	93-3%	94-28%		100-0%			97-0%	100-0%	97-0%	100-0%					1-20	100-0%	
ELKO	630GLE	230/50Hz	20-630	U	100-0%	100-0%	93-23%	90-19%	99-15%	99-8%	97-10%	98-7%	97-18%	94-8%	97-18%	94-8%	97-10%	98-7%	97-10%	98-7%	1-20	100-15%	
Eltako	EUD61NPN-UC	230/50Hz	5-400	R / L / C	100-0%	100-0%	83-7%	83-4%													1-7	100-3%	
Feller	40600 RLC	230/50Hz	20-600	U		100-0%	85-2%			97-0%	96-25%						97-0%	96-25%	97-0%	96-25%	1-6	100-0%	
Feller	40600.RC	230/50Hz			100-0%	100-0%	93-23%	90-19%	99-15%	99-8%	97-10%	98-7%	97-18%	94-8%	97-18%	94-8%	97-10%	98-7%	97-10%	98-7%	1-20	100-15%	
Feller	40200.LEDxxx	230/50Hz			100-0%	100-21%	90-28%	88-25%			96-19%	97-15%	98-27%	94-18%	98-27%	94-18%	96-19%	97-15%	96-19%	97-15%	1-20	100-27%	
Feller	40600.RL	230/50Hz				100-0%	86-21%				97-0%	97-0%					97-0%	97-0%			1-6	100-0%	
Feller	40420.RLC	230/50Hz			99-21%	100-7%	85-11%	84-7%													1-9	100-7%	
Feller	31000	230/50Hz				100-0%	93-3%	94-28%		100-0%			97-0%	100-0%	97-0%	100-0%					1-20	100-0%	
Gira	030700	230/50Hz	20-525	T	100-22%	100-27%		89-25%	99-30%	99-19%	98-23%	97-14%	96-28%	99-19%	96-28%	99-19%	98-23%	97-14%	98-23%	97-14%	2-20	100-25%	
GIRA	226200	230/50Hz				100-0%	90-15%	91-11%	99-34%	100-37%	98-29%	100-31%	99-32%	100-39%	99-32%	100-39%	98-29%	100-31%	98-29%	100-31%	1	100-14%	
Gira	117600	230/50Hz	50-420	U	99-0%	100-25%		92-31%	98-43%	100-29%	97-23%	97-21%	99-39%	95-30%	99-39%	95-30%	97-23%	97-21%	97-23%	97-21%	1-20	100-34%	
Gira	238500	230/50Hz			100-7%	100-0%	92-19%	90-16%			98-8%	99-6%		98-4%		98-4%	98-8%	99-6%	98-8%	99-6%			










*MR16 versions tested with HTM 70 transformer

DIMMER COMPATIBILITY STAR+ GLOWdim, PAR16 CRI97

Legend					STAR+ MR16 35 GLOWdim	STAR+ PAR16 50 GLOWdim 36°	Star+ CL A GLOWdim	Star+ CL A 60 GLOWdim	Star+ CL B / BA Filament GLOWdim	STAR+ CL P GLOWdim	STAR+ Edison GLOWdim	STAR+ Globe GLOWdim	STAR+ PAR16 50 CRI97									
Very good dimmability with indicated number of lamps (dimming range greater than 75%)																						
Limited dimmability with indicated number of lamps (dimming range smaller than 75%)																						
Undesired dimmability																						
Not tested																						
					EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code									
					4058075105331 / AC08773	4058075105393 / AC08774	4058075808522 / AC02140	4058075037526 / AC02143	4058075808140 / AC02154 4058075809024 / AC02155	4058075809055 / AC02228	4058075808201 / AC02156	4058075808942 / AC02157	4058075035553 / AC08013									
Dimmer					Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps		
Brand	Model	Voltage range	Power	Type																		
Gira	217400	230/50Hz	4X20-250	KNX-U	100-9%	100-30%	93-24%	94-21%												1-16	100-20%	
Hager	WUD87	230/50Hz	400	LED-U	100-4%	100-30%	89-25%	87-22%													1-10	100-20%
Hamilton	KP1X40	230/50Hz	400			99-0%	89-25%	90-25%	87-10%	93-14%			87-10%	93-14%	87-10%	93-14%						
Hugo Müller	paladin 872110 led	230/50Hz			100-0%	100-0%	97-6%	97-6%													1-7	100-4%
Jung	225 TDE	230/50Hz			100-22%	100-27%		89-25%	99-30%	99-19%	98-23%	97-14%	96-28%	99-19%	98-23%	97-14%	98-23%	97-14%	98-23%	97-14%	2-20	100-25%
Jung	225 NVDE	230/50Hz	20-500	L		100-0%	90-15%	91-11%	99-34%	100-37%	98-29%	100-31%	99-32%	100-39%	98-29%	100-31%	98-29%	100-31%	100-31%		1	100-14%
Jung	254 UDIE1	230/50Hz			99-0%	100-25%		92-31%	98-43%	100-29%	97-23%	97-21%	99-39%	95-30%	97-23%	97-23%	97-21%	97-21%	97-21%		1-20	100-34%
Jung	1224 LEDUDE	230/50Hz		LED	100-7%	100-0%	92-19%	90-16%			98-8%	99-6%		98-4%	98-8%	99-6%	98-8%	99-6%				
Jung	3904 REGHE	230/50Hz			100-9%	100-30%	93-24%	94-21%													1-16	100-20%
Legrand	665114	230/50Hz	400	U	94-11%		80-8%	80-8%	98-10%	97-3%	93-8%	88-3%	95-7%	94-3%	95-7%	94-3%	93-8%	88-3%	93-8%	88-3%	1-10	99-9%
Legrand	067083-048869-048	230/50Hz			94-11%		80-8%	80-8%	98-10%	97-3%	93-8%	88-3%	95-7%	94-3%	95-7%	94-3%	93-8%	88-3%	93-8%	88-3%	1-10	99-9%
Legrand	770061	230/50Hz	400	RL	99-29%	100-22%		90-16%				96-35%		96-42%		96-42%		96-35%		96-35%	1-8	100-20%
Legrand	099314	230/50Hz	300	RL	100-0%	100-0%					97-0%	98-0%			97-0%	98-0%		98-0%		98-0%		
Legrand	770062	230/50Hz	400	RLC	100-0%	99-0%	92-9%	91-4%	99-0%	95-0%	97-0%	97-0%	95-0%	90-0%	95-0%	90-0%	97-0%	97-0%	97-0%	97-0%		
Legrand	078405	230/50Hz	600	RL		100-0%					97-0%	96-0%		95-0%		95-0%	97-0%	96-0%	97-0%	96-0%	1-12	100-0%
MASTER	DM-DGL	230/50Hz	1000	U / LED	100-0%	100-0%	94-18%	96-18%													1-14	100-2%
MASTER	DM-2500	230/50Hz	2500	U / LED		100-0%			100-0%	99-1%	99-1%	98-0%	100-1%	98-0%	100-1%	99-1%	99-1%	99-1%	99-1%	99-1%	1-20	100-2%
Merten	MEG5136-0000	230/50Hz			100-15%	100-22%	93-30%	90-26%	99-33%		98-26%	99-21%	98-37%	98-26%	98-37%	98-26%	99-21%	98-26%	99-21%	98-26%	1-20	100-30%
Merten	MEG5139-0000	230/50Hz				100-0%		85-2%			97-0%	96-25%			97-0%	96-25%	97-0%	96-25%	97-0%	96-25%	1-6	100-0%
Merten	MEG5137-0000	230/50Hz			100-0%	100-0%	93-23%	90-19%	99-15%	99-8%	97-10%	98-7%	97-18%	94-8%	97-18%	94-8%	97-10%	98-7%	97-10%	98-7%	1-20	100-15%
Merten	MEG5134-0000	230/50Hz			100-0%	100-21%	90-28%	88-25%			96-19%	97-15%	98-27%	94-18%	98-27%	94-18%	96-19%	97-15%	96-19%	97-15%	1-20	100-27%
Merten	MEG5133-0000	230/50Hz				100-0%		86-21%			97-0%	97-0%			97-0%	97-0%	97-0%	97-0%	97-0%	97-0%	1-6	100-0%
Merten	MEG5138-0000	230/50Hz			99-21%	100-7%	85-11%	84-7%													1-9	100-7%
Merten	MEG 5170-0300	230/50Hz	10-200	U	56-0%	100-19%	66-5%															
Merten	MEG 5131	230/50Hz	40-400	L		99-0%		86-2%			96-0%	97-0%				96-0%	97-0%	96-0%	97-0%	96-0%	97-0%	
Merten	MEG 5132	230/50Hz				99-0%		86-2%			96-0%	97-0%				96-0%	97-0%	96-0%	97-0%	96-0%	97-0%	
Merten	MEG 5140	230/50Hz	9-100	L		100-0%	82-11%	82-6%	100-0%	100-0%	91-0%	94-0%	100-0%	95-0%	100-0%	95-0%	91-0%	94-0%	91-0%	94-0%		
Merten	MEG 5135	230/50Hz	60-1000	L		100-0%	93-3%	94-28%			97-0%	100-0%		97-0%	100-0%						1-20	100-0%
MK	K4501	230/50Hz	180	L	99-5%	99-0%	80-16%	81-16%	99-12%	100-15%	89-12%	95-12%	96-9%	100-14%	96-9%	100-14%	89-12%	95-12%	89-12%	95-12%	1-2	100-14%
NEXUS	881P-01	230/50Hz	400	L			92-5%	92-2%			98-0%	97-0%				98-0%	97-0%	98-0%	97-0%		1-3	100-0%

*MR16 versions tested with HTM 70 transformer

DIMMER COMPATIBILITY STAR+ GLOWdim, PAR16 CRI97

Legend					STAR+ MR16 35 GLOWdim	STAR+ PAR16 50 GLOWdim 36°	Star+ CL A GLOWdim	Star+ CL A 60 GLOWdim	Star+ CL B / BA Filament GLOWdim	STAR+ CL P GLOWdim	STAR+ Edison GLOWdim	STAR+ Globe GLOWdim	STAR+ PAR16 50 CRI97									
Very good dimmability with indicated number of lamps (dimming range greater than 75%)																						
Limited dimmability with indicated number of lamps (dimming range smaller than 75%)					EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code	EAN / Basic Code									
Undesired dimmability					4058075105331 / AC08773	4058075105393 / AC08774	4058075808522 / AC02140	4058075037526 / AC02143	4058075808140 / AC02154 4058075809024 / AC02155	4058075809055 / AC02228	4058075808201 / AC02156	4058075808942 / AC02157	4058075035553 / AC08013									
Not tested																						
Dimmer					Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps	Dimming range 1 Lamp	Dimming range 4 Lamps		
Brand	Model	Voltage range	Power	Type																		
NIKO	310-01900	230/50Hz	5-200	U	100-0%	100-0%	96-5%	95-7%	100-6%	97-5%	100-3%	97-5%	100-4%	97-5%	100-4%	97-5%	100-3%	97-5%	100-3%	1-15	100-2%	
NIKO	330-00700	230/50Hz	5-200	U	100-6%	100-13%	96-15%	95-12%												1-5	100-14%	
Odace	S520512	230/50Hz			100-0%	100-21%	90-28%	88-25%		96-19%	97-15%	98-27%	94-18%	98-27%	94-18%	96-19%	97-15%	96-19%	97-15%	1-20	100-27%	
Odace	S520511	230/50Hz				100-0%		86-21%		97-0%	97-0%					97-0%	97-0%	97-0%	97-0%	1-6	100-0%	
Odace	S520515	230/50Hz			99-21%	100-7%	85-11%	84-7%												1-9	100-7%	
Odace	S520518	230/50Hz				100-0%	82-11%	82-6%	100-0%	100-0%	91-0%	94-0%	100-0%	95-0%	100-0%	95-0%	91-0%	94-0%	91-0%	94-0%		
Osram	HTI DALI 315 DIM	230/50Hz	20-315	DALI-T	99-19%	100-22%	96-20%	96-20%	100-19%	100-13%	98-14%	100-9%	97-15%	100-12%	98-14%	100-9%	98-14%	100-9%	98-14%	100-9%	1-20	100-22%
PEHA	435 HAN	230/50Hz	60-600	L	66-0%	99-0%	82-25%	83-16%	99-7%	99-0%	90-2%	95-0%	98-6%	95-0%	98-6%	95-0%	90-2%	95-0%	90-2%	95-0%		
Schneider	400GLI	230/50Hz	40-400	T		96-0%	87-12%		96-4%	99-0%	97-1%	97-0%	94-4%	98-0%	94-4%	98-0%	97-1%	97-0%	97-1%	97-0%	1-2	100-2%
Schneider	SBD315RC	230/50Hz			100-15%	100-22%	93-30%	90-26%	99-33%		98-26%	99-21%	98-37%	98-26%	98-37%	98-26%	99-21%	98-26%	99-21%	1-20	100-30%	
Schneider	SBD600RCRL	230/50Hz				100-0%		85-2%		97-0%	96-25%					97-0%	96-25%	97-0%	96-25%	1-6	100-0%	
Schneider	SBD630RC	230/50Hz			100-0%	100-0%	93-23%	90-19%	99-15%	99-8%	97-10%	98-7%	97-18%	94-8%	97-18%	94-8%	97-10%	98-7%	97-10%	98-7%	1-20	100-15%
Schneider	SBD200LED	230/50Hz	400		100-0%	100-21%	90-28%	88-25%		96-19%	97-15%	98-27%	94-18%	98-27%	94-18%	96-19%	97-15%	96-19%	97-15%	1-20	100-27%	
Schneider	SBD600RL	230/50Hz				100-0%		86-21%		97-0%	97-0%					97-0%	97-0%	97-0%	97-0%	1-6	100-0%	
Schneider	SBD420RCRL	230/50Hz			99-21%	100-7%	85-11%	84-7%												1-9	100-7%	
Schneider	5170	230/50Hz			56-0%	100-19%	66-5%															
Schneider	SBD400RL	230/50Hz				99-0%		86-2%		96-0%	97-0%					96-0%	97-0%	96-0%	97-0%			
Schneider	SBD5PL	230/50Hz				100-0%	82-11%	82-6%	100-0%	100-0%	91-0%	94-0%	100-0%	95-0%	100-0%	95-0%	91-0%	94-0%	91-0%	94-0%		
Schneider	ATTD1000RL	230/50Hz				100-0%	93-3%	94-28%		100-0%		97-0%	100-0%	97-0%	100-0%					1-20	100-0%	
Shuttle	SDIM-T-LED-500W	230/50Hz	2-500	T & LED-T	100-0%	100-18%	92-16%	93-16%		98-7%	98-8%	96-12%	98-31%	92-17%	98-31%	92-17%	98-8%	96-12%	98-8%	96-12%	1-20	100-16%
Siemens	5TC8 284	230/50Hz	20-525	T		99-22%	94-30%	88-18%	99-36%	89-9%	98-22%	68-4%	99-31%	85-7%	99-31%	85-7%	98-22%	68-4%	98-22%	68-4%	2-20	100-13%
Siemens	5WGI-528-1AB31	230/50Hz	20-500	KNX-U	100-0%	100-0%	94-16%	92-6%												1-20	100-0%	
VADSBO	LD 220	230/50Hz	1-200	U		99-0%	96-6%	95-6%														
VARILIGHT	HQ3W	230/50Hz	400		95-0%	100-22%	78-25%	79-26%												1-10	100-34%	
VARILIGHT	JQP401W	230/50Hz	400	T			82-10%	89-11%		98-31%	97-33%	96-27%	98-44%	93-32%	98-44%	93-32%	97-33%	96-27%	97-33%	96-27%	1	95-5%
Vimar	20135	230/50Hz	3 - 100	U	100-0%	100-0%	89-13%	89-13%	100-0%	99-0%	98-0%	98-0%	99-0%	99-0%	99-0%	98-0%	98-0%	98-0%	98-0%	1-8	100-11%	
ZANO	WH401	230/50Hz	400	L			91-6%	91-3%												1-6	100-0%	
ZANO	WH251	230/50Hz	250				90-6%	90-4%			98-0%	99-0%				98-0%	99-0%	98-0%	99-0%	1-3	100-0%	
ZANO	Z GRID 700	230/50Hz	250	LED	100-0%		83-10%	82-4%	100-0%	94-0%	94-0%	84-0%	99-0%	84-0%	99-0%	84-0%	94-0%	84-0%	94-0%	84-0%	1-20	98-0%
ZANO	Z GRID 500	230/50Hz	500				91-7%	91-5%			98-0%	98-0%				98-0%	98-0%	98-0%	98-0%	1-4	100-0%	

*MR16 versions tested with HTM 70 transformer

Please Note:

- The compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment, and the results can vary in certain field applications due to a number of factors. OSRAM does not take over any responsibility, warranty or liability that this results can also achieved by using the devices under other conditions, or when using successor models of the tested devices, or different models of the same manufacturer, or when using other LED lamp types
- The absence of a dimmer from this chart does not necessarily imply incompatibility.
- Please reference the dimmer manufacturer's instructions for installation.
- LED lamps contain several electronic components. Under unfavourable conditions these can lead to acoustic noise. In case of resonance even low noise can cause audible effect. Possible factors influencing this are the installation, the design of the lamp holder and the luminaire (acoustic resonance effect) as well as the dimmer or the transformer (harmonics or electronic resonance).
- Subject to change without notice
- Errors and omission excepted
- Always make sure to use the most recent release

Application Notes:

- For best dimming results trailing edge dimmer type is recommended.
- Trailing edge type dimmer requires the neutral wire for installation.

Bitte beachten:

- Die Kompatibilitätsliste basiert auf Tests, die der Hersteller in einer im Labor simulierten Umgebung durchgeführt hat. Die Ergebnisse können aufgrund verschiedener Faktoren in manchen Praxisanwendungen abweichen. OSRAM übernimmt keinerlei Verantwortung, Garantie oder Haftung dafür, dass diese Ergebnisse tatsächlich mit den Geräten unter anderen Bedingungen, mit Nachfolgemodellen der getesteten Geräte, mit anderen Modellen desselben Herstellers oder bei Verwendung anderer LED-Lampentypen erreicht werden.
- Das Fehlen eines Dimmers in der Abbildung bedeutet nicht, dass ein Dimmer nicht kompatibel ist.
- Lesen Sie stets die Installationsanweisungen des Dimmerherstellers.
- LED-Lampen bestehen aus mehreren elektronischen Komponenten. Unter ungünstigen Bedingungen können diese Störgeräusche erzeugen. Im Resonanzfall können selbst geringe Geräusche einen hörbaren Effekt hervorrufen. Einflussfaktoren können die Installation, die Gestaltung des Lampenträgers, die Leuchte (akustischer Resonanzeffekt), der Dimmer oder der Trafo (Oberschwingungen oder elektronische Resonanz) sein.
- Änderungen vorbehalten.
- Irrtümer und Auslassungen vorbehalten.
- Vergewissern Sie sich, dass Sie stets die aktuellste Version benutzen.

Anwendungshinweis:

- Um bestmögliche Dimmergebnisse zu erzielen, wird die Verwendung von Phasenabschnitt-Dimmern empfohlen.
- Phasenabschnitt-Dimmer erfordern bei der Installation einen Neutralleiter.

LEDVANCE GmbH

Head Office:

Parkring 29-33
85748 Garching, Germany
Phone +49 89 780673-100
Fax +49 89 780673-XXX
www.ledvance.com